



Description

The FX-350 Series Intelligent Fire Alarm Control Panels are single loop addressable panels with support for up to 60 or 126 addressable points. The FX-350 Series panels are equipped with a two line by 20 character backlit LCD display, numerical keypad and an integrated UDACT/ Digital Communicator. The FX-350 Series family also includes remote LED and LCD annunciators.

The FX-350 Series panels are ideal for both new and retrofit applications. Designed for small to medium commercial, institutional and industrial occupancies, these panels are powerful enough to meet today's installation demands. The FX-350 Series panels are configurable by the keypad for onsite programming or by a PC for both onsite and remote programming. Easy to install and simple to operate and configure, the FX-350 Series panels enable the installer to configure the system to meet their specific requirements.

The FX-350 Series panels are equipped with a 5.5 Amp power supply, auxiliary resettable smoke power supply (300mA max.), an interface for a Remote Trouble Indicator (RTI-1) and an RS-485 interface for remote LCD and LED annunciators.

All FX-350 Series panels come complete with a red door, black enclosure, durable CAT-30 lock and key and space to mount up to 12 AH batteries. Optional trim rings are available for semi-flush mounting.

Features

- Listed to UL 864, 9th edition
- Single Addressable SLC Loop that supports 60 or 126 addressable points
- Points can be any combination of Addressable Sensors or Modules
- Supports Ionization Sensors, Photoelectric Sensors, Variable Heat Sensors and Multi-Sensor (Heat/Photo)
- Equipped with a 2 line by 20 character backlit LCD display, numerical keypad and an integrated UDACT/ Digital Communicator
- Digital Communicator can be configured for DACT or UDACT mode of operation
- Configurable via the front panel, PC Configurator, or remote dial up through the built-in modem
- Sensors can be configured as Alarm, Verified Alarm, Latching or Non-Latching Supervisory, Monitor and Trouble-Only
- Modules can be configured as Alarm, Latching Supervisory, Non-Latching Supervisory, Water Flow, Monitor, Trouble, Fire Drill Switch, Signal Silence Switch, Aux Disconnect Switch and Buzzer Silence Switch
- Base panel is equipped with Four Class "B" (Style "B") indicating circuits which may be configured as Class "A" (Style "Z") using a Class "A" signal converter module
- Indicating Circuits may be configured as Silenceable or Non-Silenceable for both signals and strobes
- Built-in sync protocols for the following strobe manufacturers: Mircom, Amseco, System Sensor, Gentex, Faraday and Wheelock
- Relay contacts for Common Alarm, Auxiliary/Alarm (Disconnectable), Common Supervisory and Common Trouble
- Configurable Signal Silence Inhibit, Auto Signal Silence and One-Man Walk Test
- Subsequent Alarm, Supervisory, and Trouble operation
- RS-485 Interface for Remote LED and LCD Annunciators,
- Interface for a Remote Trouble Indicator (RTI-1)
- Two event history logs comprised of a 200 event alarm log for alarm related events and a 200 event general log for all other events
- 5.5 Amp Power Supply
- Optional modules for additional internal relay circuits and City Tie/Polarity Reversal
- Optional trim rings for semi-flush mounting



S7010



7165-1477-156

ME A
approved

313-97-E


CATALOG NUMBER

5670


NOT TO BE USED FOR INSTALLATION PURPOSES.

Mircom reserves the right to make changes at any time without notice in prices, colours, materials, components, equipment, specifications and models and also to discontinue models.

Optional Adder Modules



OCAC-304 Four Indicating Circuit Class "A" Converter Module
 The OCAC-304 converts four Class "B" (Style "Y") output circuits on the FX-350 to Class "A" (Style "Z") circuits. The OCAC-304 is equipped with wire leads to connect to the FX-350 main board.



PR-300 Polarity Reversal/City Tie Module
 The PR-300 provides outputs for city box and polarity reversal applications. As a city tie module the PR-300 provides an interface between the control panel indicating circuits and a master box. As a polarity reversal module the PR-300 provides an interface between the control panel and a reverse polarity receiver.

Remote Annunciators



RAM-300LCDR Remote LCD Annunciator
 The RAM-300LCDR provides LCD remote annunciation through a 2 line by 20 character LCD display. The RAM-300LCDR provides control switches for System Reset, Signal Silence, Fire Drill and Acknowledge as well as a numeric keypad to access the menu functions. The common control functions can be disabled on a per function basis. The RAM-300LCDR has LED indicators for A.C. On, Alarm, Supervisory, Trouble and CPU Fail. The RAM-300LCD comes complete with a red enclosure and a CAT-30 Lock and key.



RAM-1016/RAM-1032 Remote LED Annunciators
 The RAM-1016 and RAM-1032 Remote LED Annunciator provide 16 or 32 points respectively of LED annunciation. Both models come standard with bi-coloured LEDs which are automatically configured for either Alarm (Red) or Supervisory (Amber). The annunciators have indicators for A.C. On, Common Trouble and Signal Silence and controls for System Reset, Lamp Test, Fire Drill, Buzzer Silence and Signal Silence. In addition both models allow for the control switches to be disabled on a per function basis. Both models mount in a BB-1001R enclosure.



RAM-208R/RAM-216R Remote LED Annunciators
 The RAM-208R and RAM-216R provide 8 or 16 points respectively of LED annunciation. Both models feature bi-coloured LEDs which are auto-configurable for either Alarm (red) or Supervisory (amber). The LED annunciators have indicators for A.C. On, Common Trouble and Signal Silence and control switches for System Reset, Signal Silence, Lamp Test and Buzzer Silence. The RAM-208R and RAM-216R are equipped with a keyswitch which allows for enabling and disabling of the Common Control functions. Both models are available in a red finish and mount in a 4-gang electrical box.

Ordering Information

Model	Description
FX-350 Series Intelligent Fire Alarm Control Panels	
FX-350-60-DR	Single Loop 60 Point Intelligent Fire Alarm Control Panel with built-in UDACT/Digital Communicator
FX-350-126-DR	Single Loop 126 Point Intelligent Fire Alarm Control Panel with built-in UDACT/Digital Communicator
FA-300TRB	Black semi-flush trim ring for FX-350 Series enclosures
Optional Adder Modules	
OCAC-304	Four Indicating Circuit Class "A" Converter Module
PR-300	Polarity Reversal/City Tie Module
Remote Annunciators	
RAM-300LCDR	Remote LCD Annunciator
RAM-1016	16 Zone Remote LED Annunciator
RAM-1032	32 Zone Remote LED Annunciator
BB-1001R	Enclosure for RAM-1016 & RAM-1032 Annunciators
RAM-208R	8 Zone Remote LED Annunciator
RAM-216R	16 Zone Remote LED Annunciator

NOT TO BE USED FOR INSTALLATION PURPOSES.



Canada
 25 Interchange Way
 Vaughan, Ontario L4K 5W3
 Telephone: (905) 660-4655
 Fax: (905) 660-4113

U.S.A.
 4575 Witmer Industrial Estates
 Niagara Falls, NY 14305
 Toll Free: (888) 660-4655
 Fax Toll Free: (888) 660-4113

Distributed by:

Web page: <http://www.mircom.com> Email: mail@mircom.com



CAT. 5670
 Rev. 1